



Moxa Inc.

Fl.4, No. 135, Lane 235, Baoqiao Rd. Xindian Dist.,
New Taipei City 23145, Taiwan, R.O.C.

TEL: 02-8919-1230

FAX: 02-8919-1231

Email: info@moxa.com

www.moxa.com

V2400-T Series Component Compatibility Guide

A list of peripheral components suitable for use with V2400-T Series computers

2015/07/06 V1.2

Copyright Notice

©2015 Moxa Inc.

All rights reserved.

Reproduction without permission is prohibited.

Trademarks

The MOXA logo is a registered trademark of Moxa Inc.

All other trademarks or registered marks in this manual belong to their respective manufacturers.

Disclaimer

Information in this document is subject to change without notice and does not represent a commitment on the part of Moxa.

Moxa provides this document as is, without warranty of any kind, either expressed or implied, including, but not limited to, its particular purpose. Moxa reserves the right to make improvements and/or changes to this manual, or to the products and/or the programs described in this manual, at any time.

Information provided in this manual is intended to be accurate and reliable. However, Moxa assumes no responsibility for its use, or for any infringements on the rights of third parties that may result from its use.

This product might include unintentional technical or typographical errors. Changes are periodically made to the information herein to correct such errors, and these changes are incorporated into new editions of the publication.

Technical Support Contact Information

www.moxa.com/support

Moxa Americas

Toll-free: 1-888-669-2872

Tel: +1-714-528-6777

Fax: +1-714-528-6778

Moxa Europe

Tel: +49-89-3 70 03 99-0

Fax: +49-89-3 70 03 99-99

Moxa India

Tel: +91-80-4172-9088

Fax: +91-80-4132-1045

Moxa China (Shanghai office)

Toll-free: 800-820-5036

Tel: +86-21-5258-9955

Fax: +86-21-5258-5505

Moxa Asia-Pacific

Tel: +886-2-8919-1230

Fax: +886-2-8919-1231

1. Introduction

The hardware components listed in this document have either been proven to provide up-to-spec performance when used with the Moxa V2400-T series of embedded computers, or which share basic design features with such components.

As Moxa computers come with different peripheral options and are engineered to differing hardware specifications, compatibility issues may sometimes arise. When paired with Moxa's V2400-T series of embedded computers, peripherals from one manufacturer may not work as well as those made by another. For this reason, Moxa provides this list of compatible components, so that users can be certain to get the reliability they expect from Moxa's V2400-T series.

2. Testing Methods

To validate a component as meeting Moxa standards of quality and environmental tolerances, five key compatibility tests may be run:

- Ambient Temperature Burn-In
- Low Temperature Hard Starts
- Heat/Humidity Burn-In
- Cyclic High-Low Temperature Burn-in
- Vibration Test

Ambient Temperature Burn-in

Components are mounted in an V2400-T computer and run through a series of stress tests at an ambient temperature of around 25°C for a specified period of time. Test periods are determined according to the class of peripherals being tested.

Low Temperature Hard Start

Components are mounted in an unpowered V2400-T computer and then the system is booted up from an extremely low temperature. The designated temperature depends on the model being tested.

Heat/Humidity Burn-in

Components are mounted in an V2400-T computer, placed in a temperature- and humidity-controlled enclosure, and then run through the burn-in test for a specific time. The temperature, humidity, and time targets vary depending on model specification.

Cyclic High-Low Temperature Burn-in

Components are mounted in an V2400-T computer, placed in a temperature controlled enclosure, and then put through the burn-in test as temperatures are cycled from very high to very low and back again over a specified period of time. The target temperatures and time vary depending on model specifications.

Vibration Test

Components are mounted in an V2400-T computer, which is bound in an electromagnetic vibrator, and then run through random vibration tests about three axes: longitudinal, transverse, and vertical. The vibration tests are compliant with EN50155/IEC61373 vibration standards.

3. Storage Endurance

Storage media, such as SSDs, CF cards, SD cards, Disk on Module, and Cfast, are composed of different electrical components. The main components related to storage endurance and life time are NAND Flash memory and NAND Flash controller.

NAND Flash memory endurance

Any NAND Flash memory has its physical program and erase (P/E) limitation, and we can specifically use the P/E cycle as well as the so-called erase count to identify it. For instance, SLC (Single level cell) flash memory has a 60,000 P/E cycle, MLC (Multi-level cell) flash memory has a 3,000 P/E cycle, and TLC NAND Flash memory has up to a 1,000 P/E cycle. Each type of flash memory has different endurance, which is why the storage life time is based on flash memory type and storage that uses SLC type flash memory could have the best endurance compared to MLC type storage. SLC storage usually supports a 5-year OEM warranty (the actual warranty period depends on the original manufacturer). Comparatively, MLC storage only supports a 1- to 3-year warranty. The major difference between SLC and MLC is that SLC NAND Flash has around 20 times lifespan of MLC, and the price may differ by a factor of 4 to 5. For systems that are expected to be highly reliable and work without fail 24 hours a day, SLC type storage is recommended, especially when the storage is running an OS and is required to provide service for a longer time, or for applications that need to frequently write data to the storage medium.

TBW

The term TeraBytes Written, abbreviated as TBW, means something similar to endurance. TBW is defined by JEDEC based on the program unit to identify its storage life time. In actual applications, storage is used for routine operations and data access. The physical P/E cycle is not appropriate for describing total rewritable data capacity, and the management efficiency of the storage controller also affects the total rewritable data capacity result. For these reasons, JEDEC defined a standard, JESD218, for SSD endurance evaluation, and uses TBW to describe the test result. By referring to this TBW value, users can easily estimate demand and select suitable storage for real-use cases. For example, when routine operations need a maximum of 20 GB and the expected storage life time is 3 years, the total rewritable data demand would be 21.9 TBW (20GB x 365 x 3). In this case, you could choose storage that has more than 21.9 TBW to match this demand; we recommend selecting a TBW that is greater than the calculated value.

Declaration for Liability Exclusion in the CCG

The specifications, warranty terms, and liability of items listed in the Moxa Component Compatibility Guide are the sole responsibility of the original manufacturers. Moxa does not any responsibility in this regard. Please visit the manufacturers' official websites for up-to-date product information before purchasing an item.

4. Compatible Components

Check the following table for validation condition codes and their description.

Test Code	Description
A	The component passed ambient temperature verification
B	The component passed low temperature verification
C	The component passed heat/humidity verification
D	The component passed cyclic high-low temperature verification
E	The component has not been tested, but shares materials and design with another component that has been verified.
F	The component passed vibration verification

The following list shows which peripherals have been tested, and for what specifications, on Moxa's embedded computers.



Moxa Inc.
 Fl.4, No. 135, Lane 235, Baoqiao Rd. Xindian Dist.,
 New Taipei City 23145, Taiwan, R.O.C.
 TEL: 02-8919-1230
 FAX: 02-8919-1231
 Email: info@moxa.com
 www.moxa.com

DOM										
Vendor	Size	Moxa's PN	Vendor's PN	Flash Brand	Flash Spec	Controller	Firmware	Warranty years	Warranty exclusion	Test Codes
InnoDisk	16 GB	N/A	DE4H-16GD31W1DT-A31	Micron	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C, D
InnoDisk	2 GB	N/A	DE4H-02GD31W1D-A31	Samsung	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C, D
InnoDisk	2 GB	N/A	DE4H-02GD31W1DR-A31	Samsung	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C, D
InnoDisk	4 GB	N/A	DE4H-04GD31W1D-A31	Samsung	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C, D
InnoDisk	4 GB	N/A	DE4H-04GD31W1DR-A31	Samsung	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C, D
InnoDisk	8 GB	N/A	DE4H-08GD31W1D-A31	Samsung	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C, D
InnoDisk	8 GB	N/A	DE4H-08GD31W1DT-A31	Micron	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C, D
Memoright	1 GB	N/A	MRDEM2B001GB7P11A0	Samsung	SLC	SM2232	K0407	5 years	N/A	E
Memoright	2 GB	N/A	MRDEM2B002GB8P11A0	Samsung	SLC	SM2232	K1124	5 years	N/A	B, C, D
Memoright	4 GB	N/A	MRDEM2B004GB0P11A0	Samsung	SLC	SM2232	K0407	5 years	N/A	B, C, D
Memoright	8 GB	1352020082040	MRDEM2B008GN2P11A0	Micron	SLC	SM2232	K0407	5 years	N/A	B, C, D
Memoright	16 GB	1352020162020	MRDEM2B016GN4P11A0	Micron	SLC	N/A	N/A	5 years	N/A	B, C, D
Memoright	32 GB	N/A	MRDEM2B032GN5P11A0	Micron	SLC	SM2232	K0407	5 years	N/A	B, C, D
Transcend	1 GB	N/A	TS1GDOM44V-S	Samsung	SLC	SM223 AC	N/A	2 years	N/A	E
Transcend	2 GB	N/A	TS2GPTM510-44V	Samsung	SLC	SM2231 AD	N/A	2 years	N/A	E
Transcend	4 GB	N/A	TS4GPTM510-44V	Samsung	SLC	SM2231 AD	N/A	2 years	N/A	E
Transcend	8 GB	N/A	TS8GPTM510-44V	Samsung	SLC	SM2231 AD	N/A	2 years	N/A	A
InnoDisk	2 GB	1352020022080	DE4H-02GD31W1DB-A31	N/A	SLC	N/A	N/A	5 years	Endurance > 60,000	B, C

CF

Vendor	Size	Moxa's PN	Vendor's PN	Flash Brand	Flash Spec	Controller	Firmware	Warranty years	Warranty exclusion	Test Codes
Transcend	128 MB	N/A	TS128MCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	256 MB	N/A	TS256MCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	512 MB	N/A	TS512MCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	1 GB	N/A	TS1GCF133	SanDisk/ Micron	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	1 GB	N/A	TS1GCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	2 GB	N/A	TS2GCF133	SanDisk/ Micron	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	2 GB	N/A	TS2GCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	4 GB	N/A	TS4GCF133	SanDisk/ Micron	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	4 GB	N/A	TS4GCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	A
Transcend	8 GB	N/A	TS8GCF400	SanDisk/ Micron	MLC	SM2236AC	N/A	2 years	N/A	E
Transcend	8 GB	N/A	TS8GCF133	SanDisk/ Micron	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	8 GB	N/A	TS8GCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	16 GB	N/A	TS16GCF1000	SanDisk/ Micron	MLC	SM2232ENAC	N/A	2 years	N/A	E
Transcend	16 GB	N/A	TS16GCF400	SanDisk/ Micron	MLC	SM2236AC	N/A	2 years	N/A	E
Transcend	16 GB	N/A	TS16GCF133	SanDisk/ Micron	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	16 GB	N/A	TS16GCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	32 GB	N/A	TS32GCF1000	SanDisk/ Micron	MLC	SM2236AC	N/A	2 years	N/A	A
Transcend	32 GB	N/A	TS32GCF400	SanDisk/ Micron	MLC	SM2236AC	N/A	2 years	N/A	A
Transcend	32 GB	N/A	TS32GCF133	SanDisk/ Micron	MLC	SM2232AD	N/A	2 years	N/A	E
Transcend	32 GB	N/A	TS32GCF200I	Samsung	MLC	SM2232AD	N/A	2 years	N/A	A
Apacer	32 GB	N/A	AP-CF032GL9FS-NR	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	A
Apacer	16 GB	N/A	AP-CF016GL9FS-NR	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	E
Apacer	8 GB	N/A	AP-CF008GL9FS-NR	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	E
Apacer	4 GB	N/A	AP-CF004GL9FS-NR	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	E
Apacer	32 GB	N/A	AP-CF032GLAFS-NR	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	A
Apacer	16 GB	N/A	AP-CF016GLAFS-NR	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	E
Apacer	8 GB	N/A	AP-CF008GLAFS-NR	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	E
Silicon Power	2 GB	N/A	SP002GBCFI000V711T	Toshiba	SLC	SMI	N/A	3 years	N/A	A
Silicon Power	1 GB	N/A	SP001GBCFI000V711T	Toshiba	SLC	SMI	N/A	3 years	N/A	E
Silicon Power	4 GB	N/A	SP004GBCFI000V602T	Toshiba	SLC	SMI	N/A	3 years	N/A	A
Silicon Power	2 GB	N/A	SP002GBCFI000V601T	Toshiba	SLC	SMI	N/A	3 years	N/A	E
Silicon Power	1 GB	N/A	SP001GBCFI000V601T	Toshiba	SLC	SMI	N/A	3 years	N/A	E



Moxa Inc.
Fl.4, No. 135, Lane 235, Baoqiao Rd. Xindian Dist.,
New Taipei City 23145, Taiwan, R.O.C.
TEL: 02-8919-1230
FAX: 02-8919-1231
Email: info@moxa.com
www.moxa.com

SSD										
Vendor	Size	Moxa's PN	Vendor's PN	Flash Brand	Flash Spec	Controller	Firmware	Warranty years	Warranty exclusion	Test Codes
Memoright	32 GB	N/A	MRSAJ6Q032GN225I00	Micron	SLC	JMF612	MRV1.1.6	5 years	N/A	B, C, D
Memoright	60 GB	N/A	MRSAD4B060GC225S00	N/A	MLC	N/A	N/A	3 years	Endurance > 3,000	E
Memoright	64 GB	N/A	MRSAJ6Q064GN225I00	Samsung	SLC	JMF612	MRV1.1.6	5 years	N/A	B, C, D
Memoright	120 GB	N/A	MRSAD4B120GC325S00	Micron	MLC	SF2281	MRV 1.50S	3 years	Endurance > 3,000	E
Memoright	240 GB	N/A	MRSAD4B240GC325S00	Micron	MLC	SF2281	MRV 1.50S	3 years	Endurance > 3,000	B, C, D
Transcend	16 GB	N/A	TS16GSSD500	Samsung	SLC	JM616	120820	2 years	N/A	E
Transcend	32 GB	N/A	TS32GSSD500	Samsung	SLC	JM616	120820	2 years	N/A	E
Transcend	64 GB	N/A	TS64GSSD320	SanDisk/ Micron	MLC	SF2281	N/A	2 years	N/A	E
Transcend	64 GB	N/A	TS64GSSD500	Samsung	SLC	JM616	120820	2 years	N/A	A
Transcend	128 GB	N/A	TS128GSSD320	SanDisk/ Micron	MLC	SF2281	N/A	2 years	N/A	E
Transcend	256 GB	N/A	TS256GSSD320	SanDisk/ Micron	MLC	SF2281	N/A	2 years	N/A	A
Apacer	64 GB	N/A	AP64GAS510SB	N/A	MLC	N/A	N/A	2 years	Endurance > 3,000	A
InnoDisk	64 GB	N/A	DES25-64GD06SW1QC	Toshiba	MLC	N/A	N/A	2 years	Endurance > 3,000	B, C, D



Moxa Inc.
Fl.4, No. 135, Lane 235, Baoqiao Rd. Xindian Dist.,
New Taipei City 23145, Taiwan, R.O.C.
TEL: 02-8919-1230
FAX: 02-8919-1231
Email: info@moxa.com
www.moxa.com

DRAM						
Vendor	Size	Moxa's PN	Vendor's PN	Chip Brand	Speed	Test Codes
DSL	1 GB	1352110012031	D2SM64162XH30ABIS	Micron	667	B, C, D
DSL	1 GB	N/A	D2SP28081XH30ABIS	ProMOS	667	B, C, D
DSL	1 GB	N/A	D2SP64162XH30AAIS	ProMOS	667	B, C, D
DSL	2 GB	1352110022070	D2SP28082XH30ABIS	ProMOS	667	B, C, D
DSL	2 GB	1352110022071	D2SM28082XH30ABIS	Micron	667	B, C, D
InnoDisk	2 GB	N/A	M2SK-2GPF2I6-B	Hynix	667	B, C, D
InnoDisk	1 GB	N/A	M2SJ-1GPF5W05-BA31	ProMOS	667	B, C, D
InnoDisk	1 GB	N/A	M2SK-1GPF5I6-BA31	ProMOS	667	B, C, D
InnoDisk	2 GB	N/A	M2SJ-2GPF2W05-B	ProMOS	667	B, C, D
InnoDisk	2 GB	N/A	M2SK-2GPF2I6-BA31	ProMOS	667	B, C, D
Unigen	1 GB	N/A	UG12T6400M8SU-6AS	Hynix	667	B, C, D
Unigen	1 GB	N/A	UG12T6408M8SU-6AS	Micron	667	B, C, D
Unigen	1 GB	N/A	UG12T6408M8SU-6AS	ProMOS	667	B, C, D
Unigen	2 GB	N/A	UG25T6408M8SU-6AP	ProMOS	667	B, C, D
Transcend	1 GB	N/A	TS128MSQ64V8U	Samsung	800	E
Transcend	2 GB	N/A	TS256MSQ64V8U	Samsung	800	A



Moxa Inc.
Fl.4, No. 135, Lane 235, Baoqiao Rd. Xindian Dist.,
New Taipei City 23145, Taiwan, R.O.C.
TEL: 02-8919-1230
FAX: 02-8919-1231
Email: info@moxa.com
www.moxa.com

HDD						
Vendor	Size	Moxa's PN	Vendor's PN	Controller	Firmware	Test Codes
HGST	1 TB	N/A	HCC541010A9E680	N/A	N/A	A
HGST	1 TB	N/A	HTS541010A9E680	N/A	N/A	A
WD	750 GB	N/A	WD7500BPKT	N/A	N/A	A
WD	1 TB	N/A	WD10JUCT	N/A	N/A	A
WD	1 TB	N/A	WD10JPVT	N/A	N/A	A
WD	1 TB	N/A	WD10SPCX	N/A	N/A	A
Samsung	2 TB	N/A	ST2000LM003	N/A	N/A	A
HGST	1 TB	N/A	HTS721010A9E630 / OJ22423	N/A	N/A	A
HGST	500 GB	N/A	HTS725050A7E630 / OJ38075	N/A	N/A	A
HGST	1 TB	N/A	HTS541010A9E650	N/A	N/A	A