VPort 351 Series

-Full motion, 1-channel MJPEG/MPEG4 industrial video encoders



- > Industrial design with -40 to 75°C operating temperature and fiber optic Ethernet port
- > Video stream up to 30 frames/sec at full D1 (720 x 480) resolution
- > Pre/post-alarm video recording function for advanced surveillance
- > Transparent PTZ control for legacy PTZ control panels and keyboards
- > 2-way (1 in, 1 out) audio supported
- > Free VPort SDK PLUS supported



: Introduction

The VPort 351 is a high performance, 1-channel industrial video encoder that provides up to full D1, full frame rate performance (NTSC: 720 x 480 @ 30 FPS; PAL: 720 x 576 @ 25 FPS) and supports a dual MJPEG/MPEG4 algorithm, making it especially well-suited for use with distributed surveillance systems in critical industrial applications. In

Specifications

Video

Video Compression: MJPEG or MPEG4 (ISO/IEC 14496-2) Video Inputs: 1, BNC connector (1.0 Vpp, 75 ohm) Video Outputs: 1, loop-through BNC connector (1.0 Vpp, 75 ohm) NTSC/PAL: Auto-sensing or manual Video Resolution and FPS (frames per second):

Max FPS QVGA 320 x 240 320 x 288 25 30 CIF 352 x 240 30 352 x 288 25 VGA 640 x 480 30 640 x 576 25 4CIF 25 704 x 480 30 704 x 576 Full D1 720 x 480 30 720 x 576 25

Video Viewing:

• Adjustable image size and quality

• Timestamp and text overlay

Audio

Audio Inputs: 1 Line-in or MIC-in with 3.5 mm phone jack Audio Outputs: 1 Line-out with 3.5 mm phone jack Audio Format: Mono, PCM

Network

Protocols: TCP, UDP, HTTP, SMTP, FTP, Telnet, NTP, DNS, DHCP, UPnP, RTP, RTSP, ICMP, IGMPv3, QoS, SNMPv1/v2c/v3, DDNS **Ethernet:** 1 10/100BaseT(X) auto negotiating RJ45 port, or 1 100BaseFX fiber port (Single/multi mode, SC connector)

Serial Port

PTZ Ports: 1, RS-232/422/485 port (terminal block connector), max. speed of 115.2 Kbps Console Port: 1, RS-232 RJ45 port addition, a continuous pre/post event trigger video record function can help system administrators determine why an alarm was triggered, and 2-way audio is provided for the convenience of real-time communication between system administrators located at the central site and engineers in the field.

GPIO

Digital Inputs: 2, max. 8 mA Low: +13 V to +30 V; High: -30 V to +3 V Relay Outputs: 2, max. 24 VDC @ 1 A

LED Indicators

STAT: Indicates if the system booted properly or not
PWR1: Power 1
PWR2: Power 2
FAULT: Can be configured to correspond to system alarm, power failure, or disconnected network
VIDEO: Video input signal active
AUDIO TEST: Audio input signal in test mode
PTZ: PTZ control signal active

Power Requirements

Input Voltage: 2 12/24 VDC or 24 VAC inputs for redundancy Power Consumption: Max. 8 W $\,$

Physical Characteristics

Housing: Metal, IP30 protection Dimensions: 52.98 x 135 x 105 mm (2.09 x 5.31 x 4.13 in) Weight: 960 g (2.11 oz) Installation: DIN-Rail mounting, wall mounting (with optional kit) Alarms

Alaliiis

Pre/Post Alarm: 9 MB memory for video recordings Video Motion Detection: Includes sensitivity tuning Video Loss: Video loss alarm Scheduling: Daily repeat timing schedule Imaging: JPEG snapshots for pre/trigger/post alarm images Email/FTP Messaging: Automatic transfer of stored images via email or FTP with event-triggered actions Custom Alarms: HTTP event servers for setting customized alarm actions

PAN/TILT/ZOOM

PTZ Camera Control: Via RS-232/422/485 PTZ port PTZ Control Functions: PAN, TILT, ZOOM, FOCUS, moving speed, preset position (max. 25 positions), and 10 custom commands PTZ Function Updates: Driver upload supported Supported Device Protocols: Pelco D, Pelco P, Dynacolor DynaDome, Custom Camera

Transparent PTZ Control: Control PTZ cameras with legacy PTZ control panel or keyboard connected to a PC or VPort decoder

Security

Password: User level password protection **Filtering:** By IP address

Environmental Limits

Operating Temperature:

Standard Models: 0 to 60°C (32 to 140°F) Wide Temp. Models: -40 to 75°C (-40 to 167°F) Storage Temperature: -40 to 85°C (-40 to 185°F) Ambient Relative Humidity: 5 to 95% (non-condensing)

Standards and Certifications

Safety: UL 508

Hazardous Location: UL/cUL Class I Division 2 Groups A/B/C/D EMI: FCC Part 15 Subpart B Class A, EN 55022 Class A

EMS:

EN 61000-4-2 (ESD), Level 2, EN 61000-4-3 (RS), Level 3, EN 61000-4-4 (EFT), Level 3, EN 61000-4-5 (Surge), Level 3, EN 61000-4-6 (CS), Level 3, EN 61000-4-8, EN 61000-4-11 Marine: DNV, GL, LR, ABS, NK Shock: IEC 60068-2-27 Freefall: IEC 60068-2-32 Vibration: IEC 60068-2-6 Note: Please check Moxa's website for the most up-to-date certification status.

MTBF (mean time between failures) Time: 272.000 hrs


Database: Telcordia (Bellcore), GB 25°C

Warranty

Warranty Period: 5 years Details: See www.moxa.com/warranty

Software Development Kit

VPort SDK PLUS: Includes CGI commands, ActiveX Control, and API library for customized applications or system integration for third-party developers (the latest version of SDK is available for download from Moxa's website).



Crdering Information

| Available Models | | Port Interface | | |
|-------------------------------------|-----------------------------------|----------------|-----------------------------|------------------------------|
| Standard Temperature (0 to 60°C) | Wide Temperature (-40 to 75°C) | 10/100BaseT(X) | Multi-mode, SC Connector | Single-mode, SC Connector |
| VPort 351 | VPort 351-T | 1 | - | - |
| VPort 351-M-SC | VPort 351-M-SC-T | - | 1 | - |
| VPort 351-S-SC | VPort 351-S-SC-T | - | - | 1 |

Optional Accessories (can be purchased separately)

SoftNVR-IA V3.0: 64-channel IP surveillance software for industrial automation applications **DR-4524/75-24/120-24:** 45/75/120 W DIN-Rail 24 VDC power supplies

MDR-40-24/60-24: 40/60 W DIN-Rail 24 VDC power supplies, -20 to 70°C operating temperature WK-46: Wall mounting kit

RK-4U: 4U-high 19" rack mounting kit

MOXA

Package Checklist

- VPort 351 video encoder
- 6-pin terminal block for 1 power input and 2 DIs
- 8-pin terminal block for the other power input and 2 relay outputs
- 5-pin terminal block for the RS-232/422/ RS-485 PTZ control port
- Documentation and software CD
- Quick installation guide (printed)
- Warranty card